

VI 200 Mega

50 - 600 WATTS CHASSIS MOUNT

Features

- **Inputs: 10 to 400VDC**
- **Output: 1 to 95VDC**
- **UL, CSA, TÜV, VDE, BABT, CE**
- **80-90% efficiency (typical)**
- **ZCS power architecture**
- **Low noise FM control**
- **Booster versions available for expanded power**



Specifications

INPUT

Input voltage See table

OUTPUT

Output voltage See table

Output power See table

PRODUCT GRADE E, C, I, M

Set point accuracy 0.5%

Low-high trim voltage 50%–110%

Output ripple pk-pk 1.5%

Load regulation 0.05%

Line regulation 0.05%

OVP set point 125%

Current limit setting 105%–125%

Remote sense Compensation 0.5V

OPERATING

Efficiency 80%–90%

Isolation input – output 3750V rms

Baseplate operating temp. 85°C

Shutdown temperature 95°C

Thermal shutdown Yes

Low noise RM topology Yes

ENVIRONMENTAL

Cooling External cooling may be required, consult sales office

STANDARDS AND APPROVALS

Safety UL1950, CSA C22.2 No. 1402C, TÜV IEC950, VDE EN60950

C-Tick AS/NZS CISPR11 Group 1 Class A

MECHANICAL

Dimensions (LxWxH) VI-L, VI-P: 125x125x15.8mm VI-M, VI-Q: 125x186x15.8mm VI-N, VI-R: 125x125x15.8mm

Selection Table Guide

Single output	VI - L	[a] [b] - [c] [d]	50-200W
	VI - M	[a] [b] - [c] [e]	100-400W
	VI - N	[a] [b] - [c] [f]	300-600W
Single output	VI - P	[a] [b] [b]- [c] [d] [d]	100-400W
	VI - Q	[a] [b] [b]- [c] [e] [d]	150-600W

Selection Table

A = INPUT VOLTAGE **B = OUTPUT VOLTAGE**

Nominal	Range	Notes		
0= 12V	10–20V	(1)	Z = 2V	2 = 15V
1= 24V	21–32V	(6)	Y = 3.3V	N = 18.5V
W= 24V	18–36V	(4)	0 = 5V	3 = 24V
2= 36V	21–56V	(3)	X = 5.2V	L = 28V
3= 48V	42–60V	(6)	W = 5.5V	J = 36V
N= 48V	36–76V	(6)	V = 5.8V	K = 40V
4= 72V	55–100V	(6)	T = 6.5V	4 = 48V
T= 110V	66–160V	(4)	R = 7.5V	H = 52V
5= 150V	100–200V	(5)	M = 10V	F = 72V
6= 300V	200–400V	(6)	1 = 12V	D = 85V
7= 150/300V	100–375V	(2)	P = 13.8V	B = 95V

C = PRODUCT GRADE **D = OUTPUT POWER/CURRENT**

	V out >5V	V out <5V
E= -10°C to +85°C	Y = 50W	Y= 10A
C= -25°C to +85°C	X = 75W	X= 15A
I= -40°C to +85°C	W = 100W	W= 20A
M= -55°C to +85°C	V = 150W	V= 30A
	U= 200W	U= 40A

E = OUTPUT POWER/CURRENT **F = OUTPUT POWER/CURRENT**

V out >5V	V out <5V	V out ?5V	V out <5V
W= 100W	W= 20A	S= 300W	S= 60A
V= 150W	V= 30A	P= 450W	P= 90A
U= 200W	U= 40A	M= 600W	M= 120A

NOTES: Maximum Output for —

	5V Outputs	>5V Outputs	<5V Outputs
(1)	75W	75W	15A
(2)	75W*	100W	20A
(3)	100W	100W	20A
(4)	150W	150W	30A
(5)	150W	200W	40A
(6)	200W	200W	40A

*100W @ 5V (20A), 300V input only.

Triple output VI - R [a] [d] - [d] [d] 150-600W
Note: For RoHS version replace VI with VE.