

DC/DC Converters

PU1000 series

800 to 1000 W



INPUT / OUTPUT

- Optimized input voltage ranges
- Input ranges from 18 to 750 Vd.c.
- Single outputs from 24 to 110 Vd.c.
- Reverse input voltage protection
- Input EN 50155 IEC 60571

FEATURES

- Current sharing
- Extra output with series diode
- External output voltage sense
- Inrush current limit
- Overvoltage protection OVP
- Alarm circuit with relay
- Inhibit input / Power down
- Output voltage adjustable on front panel

OPERATION

- Operating temperature range -25 to +55°C
- High efficiency >88%
- Fully encapsulated, meets IP20 as standard
- Convection cooled

EMC

- EN IEC 61000-6-3, Emission.
- EN IEC 61000-6-2, Immunity.
- EN IEC 61000-4-3, 10 V/m
- EN IEC 61000-4-4, 4 kV.
- EN IEC 61000-4-5 level 2 & 3.
- EN 50121-3-2 train

INPUT			
Code	Nominal inputs	Input range	Stop level
24	24 Vd.c.	18 - 32 V	< 14 V
48	48 Vd.c.	38 - 60 V	< 33 V
72	72 Vd.c.	50 - 90 V	< 45 V
110	110, 127 Vd.c.	93 - 150 V	< 77 V
220	220, 250 Vd.c.	187 - 300 V	< 154 V
440, X	440, X<750 Vd.c	<750 V	< TBD

OUTPUT		
Voltage	Current	Power
24 V	33.4 - 41.7 A	800 - 1000 W
28 V	14.3 - 17.9 A	800 - 1000 W
48 V	8.4 - 10.5 A	800 - 1000 W
60 V	6.7 - 8.4 A	800 - 1000 W
85 V	11.8 A	800 - 1000 W
110 V	7.28 - 9.09 A	800 - 1000 W

Other input ranges can be made on demand.
Input range, is the range we guarantee full output performance, $U_{out} +10\%$, $I_{out} +5\%$.
The converter works down to the stop levels.
The output voltage might decrease to approx. -10% of nominal output at the stop level.

DC OUTPUT			DC INPUT			
Voltage	Current	Power	18 - 32 V	38 - 60 V	88 - 150 V	175 - 300 V
24 V	16.7 A	800 W	PU1000 24/24			
24 V	20.9 A	1000 W		PU1000 48/24	PU1000 110/24	PU1000 220/24
28 V	14.3 A	800 W	PU1000 24/28			
28 V	17.9 A	1000 W		PU1000 48/28	PU1000 110/28	PU1000 220/28
48 V	8.4 A	800 W	PU1000 24/48			
48 V	10.5 A	1000 W		PU1000 48/48	PU1000 110/48	PU1000 220/48
60 V	6.7 A	800 W	PU1000 24/60			
60 V	8.4 A	1000 W		PU1000 48/60	PU1000 110/60	PU1000 220/60
85 V	11.8 A	1000 W			PU1000 110/85	
110 V	7.28 A	800 W	PU1000 24/110			
110 V	9.09 A	1000 W		PU1000 48/110	PU1000 110/110	PU1000 220/110

NRE might be changed if other input/output combinations are demanded

How to read our product code:

Example PU1000 110/48

PU1000= Family code and power

110 = Input voltage code 110

48 = Output voltage 48 V

FEATURES

Current sharing

Is used to balance the load between up to 10 units working in parallel. For more units contact us.

Extra output with series diode

Use the series diode output when the output is connected in parallel with other power supplies to achieve redundancy

External output voltage sense

If the output voltage regulation at the load is critical, the sense can compensate voltage drops up to 5% of the nominal voltage.

Over voltage limit/ Under voltage alarm

The built in relay changes to alarm state if the converter output voltage is not within 90 to 115 % of nominal output. An independent regulation circuit limit the output voltage.

The user can select NO or NC relay function. The relay rating is 30 V 0.3 A (d.c. or a.c.), for higher voltage please contact Polyamp.

Inhibit input / Power down

The unit allows remote start and shutdown of the converter by an external signal voltage of 5 to 12 V, max 35 mA.

Overvoltage protection OVP

The output voltage is limited to 15 % over nominal output voltage by

Reverse input voltage protection

The PU1000 has input reverse protection. On input code 24 and 48 with a parallel diode, which is dimensioned to blow an external input fuse. Other inputs use an input series thyristor.

Operating temperature range

The PU1000 series is rated to +55°C @ 100% load and continuous operation.

OPTIONAL FEATURES

Train input

Input voltage range according to train standard EN 50155 and IEC 60571, see train T-inputs below.

Inrush current limit with NTC

Reduce the inrush current during start up. the input voltage range will be affected.

Conformally coating, option I

For environment with high non condensing humidity max 98 % RH.

-40 or +70 °C operating temperature

PU1000 is designed for operation up to +70°C with derating. Temporary temperature rise e.g. as described in EN 50155 T3 up to +85°C can be accepted as the cooling system has a thermal inertia. -40°C is optional as we need to test each batch.

EN IEC 61000-4-5 level 4

External varistor + surge arrestor mounted from pole to ground. With this filter the input meets level 4 of EN IEC61000-4-5 (+/-2 kV line to line, 4 kV line to ground)

19" rack mounting bracket L89-1

To mount one PU1000 to form a full 19" rack unit 2U, see figure 1.

Mounting brackets L216-1

Mounting on flat surface in any direction. See figure 2.

Vertical mounted in 19"-rack

Up to 4 units can be mounted with L480-2 mounting bracket together with L89-1, see figure 3.

GENERAL DATA | INPUT DATA

LABEL	VALUE
Design topology	Push-Pull
Switching frequency	30 kHz
Emission / Immunity	See page 4
Electric Safety EN IEC61204-7:2018	Class I, See page 4
Ingression Protection IP	IP20
Input power at no load	Output < 50 V max 12 W Output > 50 V max 17 W
Max. accepted input ripple ¹ 50 - 400 Hz	2 % of nominal voltage
Reverse input voltage protection	Parallel diode ² < U _{in} < 60V Thyristor U _{in} > 60V
Vibration and shock	
EN/IEC 61373 Body mounted	Class B
IEC 60721-3-5	Class 5M2
IEC 60068-2-27 Bump	30 g 6 ms
IEC 60068-2-64 Random vibration	1.68gRMS
EN 45545-2 Fire protection 4.3.2 rule 1 and figure 1	HL1, HL2, HL3
Dimensions (D x W x H)	337 x 420 x 86 mm
Weight	10 kg
Power connectors	M6 Lugs
Signal connectors	0.25 - 2.5 mm ²

1. Higher ripple affects the input, contact factory
2. The converter do not start at reverse voltage
3. The output ripple might increase to 0.5% RMS of V_{out}, when IEC 61000-4-3, 10 V/m test is applied
4. Relay is also rated 300 Vdc 20 mA, switch current depends on voltage. The relay cannot be used >+70°C

OUTPUT DATA

LABEL	VALUE
Source regulation	0.1%
Load regulation (0 to 100% load) with sense connected	0.3%
Load regulation (0-100% load), no sense	0.5%
Transient recovery time for 10 to 90% load step to within 3% of nominal output voltage.	<3 ms
Output ripple (60 kHz) V _{p-p} ³	30 mVp-p
Input ripple attenuation to output 50 to 400 Hz	150:1
Emission / Immunity	See page 4
Temperature coefficient	0.02%/°C
Min output adjustment range adjustable with a 15 turn potentiometer	95 - 110%
Current limit, rectangular	105%
Remote sense	Yes
Softs start	Yes
Alarm relay rating (a.c. & d.c.)	30 V 300 mA ⁴
Start up time	1 s
Hold up time, contact factory	2 - 25 ms
Efficiency ⁵	88 - 92%
Operating temperature range at 100% load. (Convection cooling) with derating ⁶	-25 to +55°C -25 to +70°C
Storage temperature range	-40 to + 85°C

5. Lowest efficiency measured within the whole input voltage range at 100% load
6. Contact factory for derating as depends on model. The alarm relay cannot be used at +70°C

Mechanics 2U 19"-rack mounting or wall / mounting plate



Figure 1. Standard L89-1 mounting bracket for 19"-rack 2U or against a mounting plate.



Figure 3. Optional, convection cooled vertical mount in 19" cabinet 12U. Brackets L480-2 / L89-1



Figure 2. Optional L300-1 mounting brackets

CE MARK

PU1000-series meets the requirements defined by CE mark as an apparatus.

This means they meet requirements stated by EMC directive and low voltage directive (LVD) as well as 2015/863 (RoHS 3) directive.

PU1000-series is in respect to EMC, as stand alone unit. Can also be installed in any other environment by a professional installer.

PU1000-series use the electric safety standard EN IEC 61204-7:2018. On EMC it meets the requirements of EN IEC 61204-3:2018, and the generic EMC standards:

EN IEC 61000-6-2 (Immunity)

EN IEC 61000-6-3 (Emission)

SAFETY STANDARD EN IEC 61204-7:2018

ISOLATION TESTABLE LEVELS		TEST VOLTAGE
Input/Output	Input code: 24, 36, 48	2 kVd.c.
	Input code: 110, 220	3 kVa.c. 4.3 kVd.c.
Input/Signal*	Input code: 24, 36, 48	2 kVd.c.
Input/Case	Input code: 24, 36, 48	2 kVd.c.
	Input code: 110, 220	3 kVa.c. 4.3 kVd.c.
Output/Case		2 kVd.c.
Output/Signal		2 kVd.c.
Case/Signal	Input code: 24, 36, 48	2 kVd.c.
	Input code: 110, 220	3 kVa.c. 4.3 kVd.c.

Please note that product standards can demand different levels or other basic standard tests. We test according to levels below. For higher levels or other tests, contact factory.

EMC

EMC STANDARDS	TEST VOLTAGE		NOTES
Emission standards	EN IEC 61000-6-3		Commercial and light-industrial environments
	Input	Output	
EN 55016 CISPR16 (0.15 - 30 MHz)	OK	OK	Optional EN 55022 level B
EN 55016 CISPR16 (30 - 1000 MHz)	OK		Enclosure test
Immunity standards	EN IEC 61000-6-2		Industrial environments
EN IEC 61000-4-2	8 kV 15 kV		Connectors Air, Enclosure test
EN IEC 61000-4-3, see note 3	20 V/m AM-modulated		Output ripple can increase to 0.5% of Vout. Enclosure test
EN IEC 61000-4-4	±4 kV	±4 kV	
EN IEC 61000-4-5 input code 24, 48	±0.5 kV ±1 kV	±0.5 kV ±1 kV	Line-line 2 Ω Line-case 12 Ω
EN IEC 61000-4-5 input code 110, 220	±1 kV ±2 kV	±1 kV ±2 kV	Line-line 2 Ω Line-case 12 Ω
EN 50121-3-2, EN 50121-4 train	±1 kV ±2 kV	±1 kV ±2 kV	Line-line 42 Ω Line-case 42 Ω
EN IEC 61000-4-6	10 V _{RMS}	10 V _{RMS}	AM-modulated
EN IEC 61000-4-8	Not sensitive		Enclosure test
EN IEC 61000-4-10	Not sensitive		Enclosure test

We use the EMC product standard "Low voltage power supplies DC output" EN 61204-3 as base for measurement principles. The Immunity EMC levels are elevated in order to comply to EN 50121-3-2 (IEC 62236-3-2) Railway application: Rolling stock – Apparatus, and EN 50121-4 (IEC 62236-4) , Railway application: Signaling and telecommunication apparatus. Also to meet relevant parts of IEC 61000-6-5 Generic Standards – Immunity for power stations and substation environments.

SALES OFFICE & PRODUCTION

Polyamp AB
Box 229
SE-597 25 Åtvidaberg
Sweden
Phone: +46 120 854 00
info@polyamp.se | <https://polyamp.com>



Authorised, valued-added distributor

Australia & New Zealand



Powerbox Australia Pty Ltd

Sydney Head Office
4 Beaumont Road,
Mt Kuring-Gai, NSW 2080
Australia



1800 251 380



sales@powerbox.com.au



powerbox.com.au

Powerbox Pacific Ltd

New Zealand Sales Office
1a Henry Rose Place,
Albany, Auckland
New Zealand 0632



09 4158 320



sales@powerbox.co.nz



powerbox.co.nz