

SFC JENNY 1200



Article number NSN NSPA
303 000 013 6116-12-404-4148
(sand)

Set includes

- JENNY 1200 fuel cell
- Service fluid 100 ml
- User manual
- Spare air filter

Technical data

Max. charging power per day	1200 Wh / day
Nominal power	50 W
Voltage range	10 - 30 V DC
Weight	3.3 kg (7.28 lbs)
Dimensions (length x width x height)	214.5 x 96 x 264 mm (8.43 x 3.78 x 10.39 in)
Operating temperature	-20 °C to +49 °C (-4 °F to +120 °F)
Communication	SMBus
Electrical interface	Glenair # 804-005-07ZNU6-7SC

JENNY 1200 Spare Parts

Service fluid, 100 ml



Service fluid is needed for the internal process. Only refill it if requested by the fuel cell. Weight: 120 g

Article no. 150 903 001
NSN 6810-12-383-1616

Air filter unit, exchangeable



Changeable air filter to keep the process air inlet clean from sand and dust, also provides water protection. Weight: 20 g

Article no. 303 046 030
NSN 6116-12-404-2616

JENNY 600S and JENNY 1200 Cables



Li-145 Y-cable

Y-cable to power electronics and charge a Li-145 battery.
Length: 70 cm. Weight: 100 g

Article no.	905 906 072
NSN	6150-12-377-3236



BB - 2590 Y-cable

Y-cable to power electronics and charge a BB-2590 battery.
Length: 70 cm. Weight: 170 g

Article no.	905 906 074
NSN	6150-12-389-4598



Fuel Cell IN cable

Cable to connect SFC Power Manager 3G to JENNY 600S.
Length: 150 cm. Weight: 180 g

Article no.	905 906 165
NSN	6150-12-381-8016



BB - 2590 charging cable

Cable to charge a BB-2590 battery. Length: 60 cm.
Weight: 170 g

Article no.	905 906 075
NSN	NSN on request



Authorised, valued-added distributor

Australia & New Zealand



Powerbox Australia Pty Ltd

Sydney Head Office
4 Beaumont Road,
Mt Kuring-Gai, NSW 2080
Australia



1800 251 380



sales@powerbox.com.au



powerbox.com.au

Powerbox Pacific Ltd

New Zealand Sales Office
1a Henry Rose Place,
Albany, Auckland
New Zealand 0632



09 4158 320



sales@powerbox.co.nz



powerbox.co.nz